Reolink

Reolink Video Doorbell (Battery)

Smart 2K 4MP Dual-Band Wi-Fi Battery Doorbell with Headto-Toe View, Person/Vehicle/ Package Detection, Visitor Notification, Digital & Mechanical Chimes, 2-Way Audio, Wireless Doorbell

- · 2K 4MP Head-to-Toe View
- · Person/Vehicle/Package Detection
- · Works with Reolink Home Hub & WiFi NVR



Specifications

Video & Audio	
Image Sensor	1/3.11" CMOS sensor
Resolution	2048x2048 (4 megapixels) at 15 frames/sec
Video Compression	H.264/H.265
Lens	f=1.2mm F=1.8 , fixed
Field of View	 Horizontal: 150° Vertical: 150° Diagonal: 180°
Audio	Two-way audio, noise reduction, echo suppression
Power	
Battery	7000mAh rechargeable battery (Battery life varies based on settings, usage & temperature.)
Hardwired	8-24V AC, 24V DC

Interface		
Power Port	USB Type-C port	
SD Card Slot	Supports Max. 256GB microSD card	
Reset/Power Switch	YES	
Audio In/Out	Built-in 2 microphones & a speaker	
Wi-Fi		
Wireless Standard	IEEE 802.11 a/b/g/n	
Operating Frequency	2.4GHz/5GHz	
Wireless Security	WPA/WPA2	
Software		
OS Supported	PC: Windows, Mac OS; Smartphone: iOS, Android	
Protocols & Standards	SSL, TCP/IP, UDP, UPNP, SMTP, NTP, P2P	
Other Feature		
Smart Alarm	Motion detection/person/vehicle/ package detection; visitor notification	
Recording Modes	Motion-triggered recording	
Smart Home Compatibility	Google Assistant, Alexa	
Cloud Storage	Supports Reolink Cloud (available in some countries)	
Rich Notification	YESYES (Reolink Cloud subscription required)	
Quick Replies	YES	
Working Environment		
Operating Temperature	-10°C~55°C (14°F~131°F)	
Operating Humidity	10% ~ 90%	
Weatherproof	IP65 certified	
Mechanical		
Dimensions	160.0 x 48.0 x 29.5 mm	

Weight	231g
Warranty	
Limited Warranty	2-year limited warranty. For support, visit https://support.reolink.com/hc/en-us/.

Gallery & Specs



9 10 10 11 5 6 Reolink

- 1. Indicator Light
- 2. Microphone
- 3. Lens
- 4. PIR Sensor
- 5. Infrared Light
- 6. Daylight Sensor
- 7. Button Ring Light
- 8. Button
- 9. Lock Mounting Hole
- 10. Terminal Block
- 11. Power Button
- 12. Type-C Charging Port
- 13. microSD Card Slot
- 14. Speaker
- 1. Indicator Light
- 2. Microphone
- 3. Lens
- 4. PIR Sensor
- 5. Infrared Light
- 6. Daylight Sensor
- 7. Button Ring Light
- 8. Button
- 9. Lock Mounting Hole
- 10. Terminal Block
- 11. Power Button
- 12. Type-C Charging Port
- 13. microSD Card Slot
- 14. Speaker

www.reolink.com